

## LE1D motor starters

Benefits · Designed for 3-phase motor applications rated maximum 30 HP at 575 Vac · Current rating of contactor ranges from 9-40A · Circuit Breaker maximum current rating ranges from 15–95A · Available in both reversing and non-reversing versions

Maximum power AC3 duty(K W)					Rated current (A)	Type of Contactor	Code Number	Su
220V 230V	380V400V	440V	500V	660V 690V				
2.2	4	4	5.5	5.5	9	LC1D09	LE1D09	LR2D
3	5.5	5.5	7.5	7.5	12	LC1D12	LE1D12	LR2D
4	7.5	9	10	10	18	LC1D18	LE1D18	LR2D
5.5	11	11	15	15	25	LC1D25	LE1D25	LR2D
7.5	15	15	18.5	18.5	32	LC1D32	LE1D32	LR2D
11	18.5	22	22	30	40	LC1D40	LE1D40	LR2D
15	22	30	30	33	50	LC1D50	LE1D50	LR2D
18.5	30	37	37	37	65	LC1D65	LE1D65	LR2D
22	37	45	55	45	80	LC1D80	LE1D80	LR2D
25	45	45	55	45	95	LC1D95	LE1D95	LR2D

Enclosure	LE-D09 and D12	Double insulated, p
	LE-D18 and D25	Double insulated, p
	LE-D32...D25	Matel, I
Control 2 pushbuttons mounted on enclosure cover	LE-D09...D95	1 green Start Button "1"
Connections	LE-D09...D95	Pre-wired power and
Standard control circuit voltages		
Voltages	24 48 110 220 230 240 380 400	
50/60Hz	B7 E7 F7 M7 P7 U7 Q7 V7	

Product link : <https://www.nofuelpower.com/?p=1401>