

Motor circuit breaker GV2ME10

The most commonly used circuit breaker. with a choice of about 100 auxiliaries and accessories. GV2 and TeSys D or K contactors can be easily assembled as a single block with one accessory.

The high GV2 electrical endurance (up to 100 000 manoeuvres) makes it very suitable for direct manual motor control, especially GV2ME (thermal-magnetic c.b., Ith up to 32 A).

Enclosure mounting is well adapted to GV2P, with their possible extended rotary handle and visible trip indication.

Thermal-magnetic: GV2ME, GV2P, GV3P, for protection against short-circuits, overload, phase loss and phase unbalance They are conforming to, depending of the versions, IEC/EN 60947-1, IEC/EN 60947-2, IEC/EN 60947-4-1 and UL 60497-4-1, CSA 22.2 n° 60497-4-1.

Setting range(A)	MPN/SKU	220V	380V	440V	500V	660V	AC-3
		KW	KW	KW	KW	KW	kg
0.1-0.16			GV2ME01	--	--	--	--
0.16-0.25			GV2ME02	--	--	--	--
0.25-0.4			GV2ME03	--	--	--	--
0.4-0.63			GV2ME04	--	--	--	0.37
0.63-1.0			GV2ME05	--	--	0.37	0.37
1.0-1.6			GV2ME06	--	0.37	0.55	0.75
1.6-2.5			GV2ME07	0.37	0.75	1.1	1.1
2.5-4.0			GV2ME08	0.75	1.5	1.5	2.2
4-6.3			GV2ME10	1.1	2.2	3	3.7
6.0-10.0			GV2ME14	2.2	4	4	5.5
9.0-14.0			GV2ME16	3	5.5	7.5	7.5
13.0-18.0			GV2ME20	4	7.5	9	9
17.0-23.0			GV2ME21	5.5	11	11	11
20.0-25.0			GV2ME22	5.5	11	11	15
24.0-32.0			GV2ME32	7.5	15	15	18.5

Product link : <https://www.nofuelpower.com/?p=1467>