

---

## Motor circuit breaker GV2P06

The most commonly used circuit breaker. with a choice of about 100 auxiliaries and accessories. GV2 and TeSys D or K contactors can be easily assembled as a single block with one accessory. The high GV2 electrical endurance (up to 100 000 manoeuvres) makes it very suitable for direct manual motor control, especially GV2ME (thermal-magnetic c.b., lth up to 32 A). Enclosure mounting is well adapted to GV2P, with their possible extended rotary handle and visible trip indication.

Thermal-magnetic: GV2ME, GV2P, GV3P, for protection against short-circuits, overload, phase loss and phase unbalance They are conforming to, depending of the versions, IEC/EN 60947-1, IEC/EN 60947-2, IEC/EN 60947-4-1 and UL 60497-4-1, CSA 22.2 n° 60497-4-1.

0.16-0.25	GV2P02	--	--	--	--	--	
0.25-0.4	GV2P03	--	--	--	--	--	
0.4-0.63	GV2P04	--	--	--	--	0.37	
0.63-1.0	GV2P05	--	--	0.37	0.37	0.55	
1.0-1.6	GV2P06	--	0.37	0.55	0.75	1.1	
1.6-2.5	GV2P07	0.37	0.75	1.1	1.1	1.5	
2.5-4.0	GV2P08	0.75	1.5	1.5	2.2	3	
4-6.3	GV2P10	1.1	2.2	3	3.7	4	
6.0-10.0	GV2P14	2.2	4	4	5.5	7.5	
9.0-14.0	GV2P16	3	5.5	7.5	7.5	9	
13.0-18.0	GV2P20	4	7.5	9	9	11	
17.0-23.0	GV2P21	5.5	11	11	11	15	
20.0-25.0	GV2P22	5.5	11	11	15	18.5	
24.0-32.0	GV2P32	7.5	15	15	18.5	26	

Product link : <https://www.nofuelpower.com/?p=1491>